

SPECIFICATION

TO ALL WHOM IT MAY CONCERN:

BE IT KNOWN THAT WE, Shigemi Kurashima, a citizen of Japan residing at Shinagawa, Tokyo, Japan, Masahiro Yanagi, a citizen of Japan residing at Shinagawa, Tokyo, Japan, Masaya Endo, a citizen of Japan residing at Shinagawa, Tokyo, Japan, Shinobu Sasaki, a citizen of Japan residing at Shinagawa, Tokyo, Japan and Norio Endo, a citizen of Japan residing at Shinagawa, Tokyo, Japan have invented certain new and useful improvements in

INPUT SYSTEM AND INPUT DEVICE

of which the following is a specification : -

TITLE OF THE INVENTION

INPUT SYSTEM AND INPUT DEVICE

BACKGROUND OF THE INVENTION

5 1. Field of the Invention

The present invention generally relates to input systems and input devices, and more particularly to an input system in which information input by radio communication is transmitted and an
10 input device that transmits information input by radio communication.

Recently, there has been a demand for wireless HIDs (Human Interface Devices) to improve the operability of computers. Radio communication
15 methods employing infrared (Ir) lights or radio frequency (RF) electromagnetic waves have been conventionally employed in the wireless HIDs. In these methods, methods employing the RF electromagnetic waves have received attention since
20 the RF electromagnetic waves have good transmissiveness.

2. Description of the Related Art

However, legal restrictions on radio waves restrict transmission power in radio communication
25 employing the RF electromagnetic waves, which makes a communicable distance of the RF radio communication insufficient. Further, the legal restrictions prevent sufficient electric field strength to receive radio waves from being obtained.
30 Therefore, the majority of conventional wireless input devices employ the Ir lights.

SUMMARY OF THE INVENTION

35 It is a general object of the present invention to provide an input system and an input device in which the above-described disadvantage is eliminated.

A more specific object of the present invention is to provide an input system and an input device which realize good information communication.

The above objects of the present invention
5 are achieved by an input system including an information generation part which generates input information based on a given input operation, a transmission part which transmits signals generated by having a plurality of different carrier
10 frequencies modulated with the input information, and a reception part which receives the transmitted signals and demodulates the signals into the input information.

According to the above-described input
15 system, since the signals generated by having the carrier frequencies modulated with the input information are transmitted, a received signal level can be raised even if each carrier frequency has weak electric field strength.

The above objects of the present invention
20 are also achieved by an input system including an information generation part which generates input information based on a given input operation, a transmission part which transmits a signal generated
25 by having a carrier frequency modulated with the input information, a plurality of wave direction parts which are provided close to the transmission part so as to provide the signal transmitted from the transmission part with directivity, and a
30 reception part which receives the transmitted signal and demodulates the signal into the input information.

According to the above-described input
35 system, space diversity effect can be obtained by outputting the same data of the same carrier frequency from the wave direction parts. Therefore, an efficient signal transmission can be performed

irrespective of an input device state.

The above objects of the present invention are also achieved by an input device including an information generation part which generates input
5 information based on a given input operation, and a transmission part which transmits signals generated by having a plurality of different carrier frequencies modulated with the input information.

According to the above-described input
10 device, since the signals generated by having the carrier frequencies modulated with the input information are transmitted, a received signal level can be raised even if each carrier frequency has weak electric field strength.

15 The above objects of the present invention are further achieved by an input device including an information generation part which generates input information based on a given input operation, a transmission part which transmits a signal generated
20 by having a carrier frequency modulated with the input information, and a plurality of wave direction parts which are provided close to the transmission part so as to provide the signal transmitted from the transmission part with directivity.

25 According to the above-described input device, space diversity effect can be obtained by outputting the same data of the same carrier frequency from the wave direction parts. Therefore, an efficient signal transmission can be performed
30 irrespective of an input device state.

BRIEF DESCRIPTION OF THE DRAWINGS

Other objects, features and advantages of the present invention will become more apparent from
35 the following detailed description when read in conjunction with the accompanying drawings, in which:

FIG. 1 is a block diagram of an input system according to a first embodiment of the present invention;

FIG. 2 is a block diagram of a first transmission circuit of the first embodiment;

FIG. 3 is a diagram showing a structure of each of matching circuits of the first transmission circuit and a second transmission circuit of the first embodiment;

FIG. 4 is a diagram showing transmission signal strength for carrier frequencies f_1 and f_2 of the first embodiment;

FIGS. 5A and 5B are a top plan view and a side view of an input device of the first embodiment, respectively;

FIG. 6 is a diagram showing characteristics of electric field strengths of the carrier frequencies f_1 and f_2 according to a distance between a reception antenna and a first antenna and a distance between the reception antenna and a second antenna, respectively;

FIG. 7 is a block diagram of an input system according to a second embodiment of the present invention;

FIG. 8 is a block diagram of an input system according to a third embodiment of the present invention;

FIG. 9 is a block diagram of a transmission circuit of the third embodiment;

FIG. 10 is a diagram showing an input system according to a fourth embodiment of the present invention;

FIG. 11 is a block diagram of an input system according to a fifth embodiment of the present invention;

FIGS. 12A and 12B are a top plan view and a side view of an input device of the fifth

embodiment, respectively;

FIG. 13 is a diagram showing an input system according to a sixth embodiment of the present invention;

5 FIG. 14 is a block diagram of the input system of the sixth embodiment;

FIGS. 15A and 15B are a top plan view and a side view of an input device of the sixth embodiment, respectively;

10 FIG. 16 is a block diagram of an input system according to a seventh embodiment of the present invention;

FIG. 17 is a diagram showing an input device 601 of the seventh embodiment;

15 FIG. 18 is an exploded perspective view of a membrane switch part that is a variation of a membrane switch part of the seventh embodiment;

FIG. 19 is a block diagram of an input system according to an eighth embodiment of the present invention; and

20 FIG. 20 is a block diagram of an input system according to a ninth embodiment of the present invention.

25 DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

A description will now be given, with reference to the accompanying drawings, of embodiments of the present invention.

30 FIG. 1 is a block diagram of an input system 1 according to a first embodiment of the present invention.

The input system 1 is applied as an input system for a computer. The input system 1 includes an input device 11 and a reception circuit 12.

35 Information input from the input device 11 is supplied via two radio communication paths to the reception circuit 12. The reception circuit 12

supplies the information from the input device 11 to the computer.

The input device 11 is a mouse and includes a coordinate detection ball 21, sensors 22 and 23, switches 24 and 25, a microprogram control unit (MCU) 26, first and second transmission circuits 27 and 28, first and second antennas 29 and 30, and a power supply 31.

Each of the sensors 22 and 23 includes a rotary encoder and generates pulses whose number corresponds to a rotational displacement amount of the coordinate detection ball 21. The detection results of each of the sensors 22 and 23 are supplied to the MCU 26. The MCU 26 computes displacement amounts in X and Y directions based on the pulses supplied from the sensors 22 and 23, respectively. The MCU 26 detects a click operation by turning the switches 24 and 25 ON.

The MCU 26 generates input information corresponding to an input operation of a user based on the pulses supplied from the sensors 22 and 23, and "ON" signals supplied from the switches 24 and 25. Then, the MCU 26 supplies the input information to the first and second transmission circuits 27 and 28.

The first transmission circuit 27 has a first carrier frequency f_1 modulated with the input information supplied from the MCU 26 by using a predetermined modulation method such as FSK (Frequency Shift Keying) or ASK (Amplitude Shift Keying). The second transmission circuit 28 has a second carrier frequency f_2 modulated with the input information supplied from the MCU 26 by using a predetermined modulation method such as FSK (Frequency Shift Keying) or ASK (Amplitude Shift Keying). The second carrier frequency f_2 is higher than the first carrier frequency f_1 . The modulation

methods used in the first and second transmission circuits 27 and 28 are not limited to FSK or ASK, and other modulation methods may be used. That is, the first and second transmission circuits 27 and 28 are not limited in the modulation methods. A spread spectrum may also be used for the modulation.

FIG. 2 is a block diagram of the first transmission circuit 27 according to the first embodiment of the present invention.

The first transmission circuit 27 shown in FIG. 2 includes an oscillator circuit 41, an amplifier 42, and a matching circuit 43, and employs a modulation method of ASK. The second transmission circuit 28 has the same structure as the first transmission circuit 28.

The oscillator circuits 41 of the first and second transmission circuits 27 and 28 generate carrier waves of the first and second carrier frequencies f_1 and f_2 , respectively. The carrier waves generated by the oscillator circuits 41 are supplied to the respective amplifiers 42.

Each of the amplifiers 42 of the first and second transmission circuits 27 and 28 forms an amplitude modulation circuit, and amplifies the carrier wave by an amplification factor corresponding to the input information supplied from the MCU 26 so as to have the carrier wave amplitude-modulated with an information signal. The output signals of the amplifiers 42 of the first and second transmission circuits 27 and 28 are supplied via the respective matching circuits 43 to the first and second antennas 29 and 30, respectively.

Each of the matching circuits 43 of the first and second transmission circuits 27 and 28 performs impedance matching. The values of the circuit elements of each of the matching circuits 43 are provided so that an optimum impedance matching

is performed when the user operates the mouse for input operations.

FIG. 3 is a diagram showing a structure of each of the matching circuits 43 of the first and second transmission circuits 27 and 28 according to the first embodiment of the present invention.

The matching circuits 43 of the first transmission circuit 27 has a capacitor C1 connected in series between the amplifier 42 and the first antenna 29, and a capacitor C2 connected between a connection of the capacitor C1 and the first antenna 29, and a ground. Further, if the user touches the mouse for an operation, a capacitor Ch, for instance, is added between the matching circuit 43 and the first antenna 29. The capacitance of each of the capacitors C1 and C2 is provided in consideration of the capacitance of the capacitor Ch. Thereby, the optimum impedance matching can be achieved when the user operates the mouse for input operations. The matching circuit 43 of the second transmission circuit 28 has the same structure as that of the first transmission circuit 27.

The first and second transmission circuits 27 and 28 employ the different carrier frequencies f1 and f2 ($> f1$), respectively.

Transmission signals modulated in the respective transmission circuits 27 and 28 are radiated outside from the first and second antennas 29 and 30, respectively. At this time, the input information supplied from the MCU 26 is radiated from the first and second antennas 29 and 30, respectively, substantially at the same time.

FIG. 4 is a diagram showing transmission signal strength for the carrier frequencies f1 and f2 of the first embodiment of the present invention. In FIG. 4, a strength P0 is a value specified by the legal restrictions on radio waves.

The strengths of radio waves radiated from the first and second antennas 29 and 30 are adjusted so as not to exceed the specified value P_0 as shown in FIG. 4. The adjustment of the radio wave
5 strength is performed, for instance, by setting the amplification factor of each of the amplifiers 42.

FIGS. 5A and 5B are a top plan view and a side view of the input device 11, respectively, showing an arrangement of the antennas 29 and 30 of
10 the first embodiment of the present invention.

The first and second antennas 29 and 30 are arranged apart from each other by a distance L in a direction in which the first and second antennas 29 and 30 are desired to have directivity.
15 Letting a cycle of a carrier frequency be λ , the distance L is set to approximately $1/2\lambda$ or below, specifically, $1/8\lambda$, for instance.

Suppose that each of the carrier frequencies f_1 and f_2 of the first and second
20 transmission circuits 27 and 28 is approximately 320 MHz, $1/8\lambda$ is approximately 10 cm.

By thus setting the distance L between the first and second antennas 29 and 30 to approximately $1/8\lambda$, the radio waves radiated from the first and
25 second antennas 29 and 30 are allowed to compensate for a decrease in each other's electric field strength according to a communication distance.

FIG. 6 is a diagram showing the characteristics of the electric field strengths of
30 the carrier frequencies f_1 and f_2 according to a distance between a reception antenna and the first antenna 29 and a distance between the reception antenna and the second antenna 30, respectively. In FIG. 6, solid and broken lines indicate the electric
35 field strengths of the carrier frequencies f_1 and f_2 radiated from the first and second antennas 29 and 30, respectively.

By setting the distance L between the first and second antennas 29 and 30 to approximately $1/8\lambda$, the characteristics of the electric field strengths of the carrier frequencies f_1 and f_2 are obtained as shown in FIG. 6. As shown in FIG. 6, the electric field strength of the radio wave radiated from the second antenna 30 reaches a peak level at a distance S_1 where the electric field strength of the radio wave radiated from the first antenna 29 reaches a lowest level. On the other hand, the electric field strength of the radio wave radiated from the first antenna 29 reaches a peak level at a distance S_2 where the electric field strength of the radio wave radiated from the second antenna 30 reaches a lowest level. Thus, the radio waves can compensate for a decrease in each other's electric field strength. Therefore, the electric field strengths of the radio waves are prevented from being lowered significantly irrespective of a position of the mouse. Thereby, the input information is reliably transmittable to a receiver.

The radio waves radiated from the first and second antennas 29 and 30 are received by the reception circuit 12 shown in FIG. 1.

The reception circuit 12 includes an amplitude demodulation circuit, and receives the radio waves from the first and second antennas 29 and 30 to demodulate the transmission signals into the original information signals. At this time, the reception circuit 12 is allowed to selectively receive and demodulate the transmission signals of the carrier frequencies f_1 and f_2 . Therefore, the output signal of the reception circuit 12 is the combination of the information signals obtained by demodulating the modulated waves of the carrier frequencies f_1 and f_2 , respectively. Therefore, the output signal of the reception circuit 12 is

approximately twice as strong as a signal obtained by demodulating a modulated wave of a single carrier frequency. The information signals obtained by demodulation in the reception circuit 12 are
5 supplied to the computer, where the information signals are recognized as the input information to be used for control of coordinate positions of a pointer or instructions on icon selection.

Thus, according to the input system 1 of
10 this embodiment, signals can be received efficiently with weaker electric field strength.

In this embodiment, the reception circuit 12 is formed to simultaneously receive and demodulate modulated waves of different carrier
15 frequencies. However, a reception part may be provided for each of the modulated waves of the different carrier frequencies.

FIG. 7 is a block diagram of an input system 100 according to a second embodiment of the present invention. In FIG. 7, the same elements as those of FIG. 1 are referred to by the same numerals,
20 and a description thereof will be omitted.

The input system 100 differs from the input system 1 of FIG. 1 in a reception circuit
25 structure. A reception circuit 110 of this embodiment includes first and second reception parts 111 and 112 for receiving the radio waves of the first and second carrier frequencies f_1 and f_2 transmitted from the first and second antennas 29
30 and 30, respectively, and a synthesis part 113 that synthesizes first and second received signals from the first and second reception parts 111 and 112, respectively.

According to this embodiment, the radio
35 waves of the first and second carrier frequencies f_1 and f_2 are individually received and then synthesized. Therefore, the radio waves are

efficiently received and demodulated, so that received signal levels can be raised.

According to the first and second embodiments, the separate first and second transmission circuits 27 and 28 are provided. However, a signal transmission may be performed through a single transmission circuit by alternating between the first and second carrier frequencies f1 and f2.

FIG. 8 is a block diagram of an input system 200 according to a third embodiment of the present invention. In FIG. 8, the same elements as those of FIG. 1 are referred to by the same numerals, and a description thereof will be omitted.

The input system 200 differs from the input system 1 of FIG. 1 in an input device structure. An input device 210 of this embodiment includes a transmission circuit 211 and a switching circuit 212 instead of the first and second transmission circuits 27 and 28 of the input device 11 of FIG. 1.

A switching control signal Sc supplied from the MCU 26 allows the transmission circuit 211 to transmit a signal alternately to the first and second antennas 29 and 30. By thus outputting the same data of the same carrier frequency alternately from the first and second antennas 29 and 30, a space diversity effect can be produced. Therefore, a signal can be efficiently transmitted irrespective of a state of the input device 210.

FIG. 9 is a block diagram of the transmission circuit 211 of the third embodiment of the present invention. In FIG. 9, the same elements as those of FIG. 2 are referred to by the same numerals, and a description thereof will be omitted.

The transmission circuit 211 of this embodiment differs from the first or second

transmission circuit 27 or 28 shown in FIG. 2 in an oscillator circuit structure. An oscillator circuit 221 of this embodiment includes a voltage-controlled oscillator (VCO) 231, a switching circuit 232, and
5 constant-voltage power supplies 233 and 234.

A voltage V1 or V2 from the constant-voltage power supply 233 or 234 is applied to the VCO 231 through the switching circuit 232. The VCO 231 oscillates at the first carrier frequency f1 if
10 the voltage V1 from the constant-voltage power supply 233 is applied thereto, and oscillates at the second carrier frequency f2 if the voltage V2 from the constant-voltage power supply 234 is applied thereto.

15 The switching circuit 232 is switched so as to apply the voltage V1 from the constant-voltage power supply 233 to the VCO 231 if the level of the switching control signal Sc supplied from the MCU 26 is HIGH, and the voltage V2 from the constant-voltage power supply 234 to the VCO 231 if the level
20 of the switching control signal Sc is LOW.

The switching circuit 212 supplies the output signal of the transmission circuit 211 to the first antenna 29 if the level of the switching
25 control signal Sc is HIGH, and to the second antenna 30 if the level of the switching control signal Sc is LOW.

At this point, the cycle of the switching control signal Sc supplied from the MCU 26 to the
30 transmission circuit 211 and the switching circuit 212 is sufficiently short compared with that of the information signal so that a switching between the first and second carrier frequencies f1 and f2 is performed with the information signal being in the
35 same state.

The switching control signal Sc may be diffusion data.

According to this embodiment, a signal transmission can be performed through the single transmission circuit 211, thus simplifying a structure of the input device 210 and reducing the production cost thereof.

Further, in order to improve transmission efficiency, the input device 1, 100, or 200 may be operated on a special mouse pad (pad member) therefor.

FIG. 10 is a diagram showing an input system 300 according a fourth embodiment of the present invention. In FIG. 10, the same elements as those of FIG. 1 are referred to by the same numerals, and a description thereof will be omitted.

The input system 300 includes the input device 11 operated on a mouse pad (pad member) 301. The mouse pad 301 is defined by a reflector 302 and a director 303. The reflector 302 is formed of conductive wire, and is provided on an end portion of the mouse pad 301 in a direction indicated by arrow A2. A length L302 of the reflector 302 is given by the following expression:

$$L_{302} \leq 0.50 \times (\lambda \times a) = 0.50\lambda'$$

where λ is a wavelength of a transmission wave, a is a wavelength shortening rate, and $\lambda' = (\lambda \times a)$.

The director 303 is formed of conductive wire, and is provided on an end portion of the mouse pad 301 in a direction indicated by arrow A1. A length L303 of the director 303 is given by the following expression:

$$L_{303} \leq 0.43 \times (\lambda \times a) = 0.43\lambda'$$

A distance d between the reflector 302 and

the director 303 is given by the following expression:

$$0.14\lambda' \leq d \leq 0.4\lambda'$$

5

According to the above-described structure, the transmission wave radiated from the input device 11 has directivity in the A1 direction, so that the transmission wave is efficiently transmitted to the reception circuit 12 by providing the reception antenna in the A1 direction.

The lengths L302 and L303 of the above-described reflector 302 and the director 303, and the distance d between the reflector 302 and the director 303 are based on the Yagi-Uda antenna theory.

In this embodiment, the directivity is produced by embedding the conductive wire in the mouse pad 301. However, the directivity can be obtained by embedding or applying the conductive wire in or on the operation surface of a desk on which the input device 11 is operated.

Further, in this embodiment, it is possible to have the user serve as an antenna by providing a conductor on the surface of the input device 11 so that the signal is transmitted via the conductor to the user touching the conductor. The same effect can be obtained by operating the input device 100 or 200 on the mouse pad 301.

FIG. 11 is a block diagram of an input system 400 according to a fifth embodiment of the present invention. FIGS. 12A and 12B are a top plan view and a side view of an input device 401 of the input system 400, respectively. In FIGS. 11, 12A, and 12B, the same elements as those of FIGS. 1, 5A, and 5B are referred to by the same numerals, and a description thereof will be omitted.

The input device 401 includes a conductive part 402 to which the output signals of the first and second transmission circuits 27 and 28 are supplied. The conductive part 402 includes a
5 conductor such as a metal plate, and is exposed on the surface of a housing 403 of the input device 401 so as to be touched by the user.

According to this embodiment, a signal transmission can be performed efficiently with the
10 user touching the conductive part 402.

Although the signal transmission is performed via the user touching the conductive part 402 in this embodiment, the transmission signal may be supplied to an operation surface on which the
15 input device 401 is operated by forming the operation surface of a conductor and contacting a conductor formed on the surface of the input device 401 with the operation surface.

FIG. 13 is a diagram showing an input
20 system 500 according to a sixth embodiment of the present invention. FIG. 14 is a block diagram of the input system 500. FIGS. 15A and 15B are a top plan view and a side view of an input device 501 of the input system 500, respectively. In FIGS. 13, 14,
25 15A, and 15B, the same elements as those of FIGS. 1, 5A, and 5B are referred to by the same numerals, and a description thereof will be omitted.

The input system 500 includes the input device 501 operated on a conductive operation plate
30 502. The input device 501 includes a conductive part 503 to which the output signals of the first and second transmission circuits 27 and 28 are supplied. The conductive part 503 includes a conductor such as a metal plate, and is exposed on
35 the bottom surface of a housing 504 of the input device 501 so as to contact the operation plate 502.

According to this embodiment, the

conductive part 503 contacts the operation plate 502 to have the operation plate 502 serve as an antenna. Therefore, a signal transmission can be performed efficiently.

5 In this embodiment, the input device 501 is a mouse. However, the input device 501 is not limited to a mouse, but can be realized in the form of a keyboard.

10 FIG. 16 is a block diagram of an input system 600 according to a seventh embodiment of the present invention. FIG. 17 is a diagram showing an input device 601 of the input system 600. In FIGS. 16 and 17, the same elements as those of FIG. 1 are referred to by the same numerals, and a description
15 thereof will be omitted.

20 The input system 600 differs from the input system 1 in an input device structure. The input device 601 includes a key entry part 602 and a conductive part 603 instead of the coordinate detection ball 21, the sensors 22 and 23, and the switches 24 and 25.

25 The key entry part 602 includes key buttons 611, a membrane switch part 612 including individual membrane switches. A membrane switch is switched ON by pressing down a corresponding one of the key buttons 611, and a code corresponding to the membrane switch is recognized by the MCU 26. The code recognized by the MCU 26 is subjected to modulation in the first and second transmission
30 circuits 27 and 28 to be transmitted from the first and second antennas 29 and 30 and from the user via the conductive part 603. The conductive part 603 is exposed on a palm rest 621 so as to be contacted by the user performing input operations by keying.

35 The first antenna 29 is provided on an end portion of the input device 601 in a direction indicated by arrow B1, and the second antenna 30 is

placed at a distance L from the first antenna 29 in a direction indicated by arrow B2.

According to this embodiment, a signal transmission can be performed efficiently because
5 not only the first and second antennas 29 and 30 transmit the transmission waves but also the user transmits the transmission wave by contacting the conductive part 603.

The first and second antennas 29 and 30
10 may be formed in a pattern on the membrane switch part 612.

FIG. 18 is an exploded perspective view of a membrane switch part 701 that is a variation of the membrane switch part 612 of the seventh
15 embodiment.

The membrane switch part 701 includes an upper membrane sheet 711, a lower membrane sheet 712, and an insulating sheet 713. The upper membrane sheet 711 includes a resin sheet 720 on which a
20 wiring pattern 721, electrodes 722, and an antenna pattern 723 forming the first antenna 29 are formed.

The lower membrane sheet 712 includes a resin sheet 730 on which a wiring pattern 731, electrodes 732, and an antenna pattern 733 forming
25 the second antenna 30 are formed. The electrodes 732 are formed to oppose the electrodes 722 of the upper membrane sheet 711.

The insulating sheet 713 is interposed between the upper and lower membrane sheets 711 and
30 712 to insulate the wiring patterns 721 and 731. Hole parts 741 are formed in the insulating sheet 713 to form spaces between the electrodes 722 and 732. The key buttons 611 are provided above the electrodes 722 and 732. When the key buttons 611
35 are not pressed down, the electrodes 722 and 732 are separated by the spaces formed therebetween. When one of the key buttons 611 is pressed down, the

corresponding electrodes 722 and 732 contact so that an electric current flows therebetween. As a result, the pressed one of the key buttons 611 is detected.

The first and second antennas 29 and 30 are formed to be loop antennas by the antenna patterns 723 and 733, respectively.

According to this variation, it is not necessary to separately provide the first and second antennas 29 and 30 because the first and second antennas 29 and 30 are formed as the antenna patterns 723 and 733.

In the first through seventh embodiments, only two antennas are provided for simplicity purposes. However, the number of antennas is not limited to two, and more than two antennas or transmission or reception circuits may be provided.

FIG. 19 is a block diagram of an input system 700 according to an eighth embodiment of the present invention.

As shown in FIG. 19, a transmission signal of a single carrier frequency transmitted from the first transmission circuit 27 may be output from a plurality of antennas 29-1 through 29-n. This structure produces space diversity effect, thus realizing an efficient signal transmission irrespective of a state of an input device 701.

FIG. 20 is a block diagram of an input system 800 according to a ninth embodiment of the present invention.

As shown in FIG. 20, the antennas 29-1 through 29-n may have corresponding transmission circuits 27-1 through 27-n. This structure allows the output strength of each of the antennas 29-1 through 29-n to be adjusted easily to an optimum value.

Further, a plurality of antennas AR-1 through AR-n may be provided on the side of the

reception circuit 12. This structure makes space diversity more effective.

The present invention is not limited to the specifically disclosed embodiments, but
5 variations and modifications may be made without departing from the scope of the present invention.

The present application is based on Japanese priority application No. 2000-346994 filed on November 14, 2000, the entire contents of which
10 are hereby incorporated by reference.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
221